

**43CPC004EN****ERACLE CONVENTIONAL CONTROL PANEL WITH 4 ZONES**

Eracle 4 zones is a conventional fire alarm panel certificated by EN54-2 and 4. Up to 32 detectors and manual call points can be connected to each fire zone. The panel is provided with robust plastic cabinet and with LED display. The panel shows fire and faults alarm for each detection zone plus generale information such as alarm, fault, sounder disable, zones disable, test, power. Commands available are test, sounder silence, reset, walk test. Access protected by key.



**43CPC004EN**

**ERACLE CONVENTIONAL CONTROL PANEL WITH 4 ZONES**

**MAIN FEATURES**

Comelit sensors and buttons per zone (max.) (n°)	32
Protection lev. 2	Mechanical key
EN regulations	EN54-2, EN54-4

**HARDWARE SPECIFICATIONS**

Case	Plastic
Product weight without battery (g)	2100
Operating temperature (°C)	-5 ÷ 40
Operating humidity (RH max @40°C) (%)	0 ÷ 96
Storage temperature (°C)	-20 ÷ 60
Cross-section for terminals (mm)	1 ÷ 2.5

**ELECTRICAL SPECIFICATIONS**

Backup power supply (batteries not supplied)	1x 12VDC, 7Ah, 2A fuse
Mains power absorption (mA)	50
Max. absorption of connected devices with charged battery (A)	0.7
FAULT relay and ALARM relay outputs	3A@120 VAC, 3A@60 VDC
Monitored outputs	2 (0.3A max each)
Circuit outputs for sirens	0.5A@24VDC, fuse 0.5A (PTC)
Alarm zone thresholds (mA)	10 ÷ 110
Short-circuit zone power supply and thresholds	>110
Fault or Open circuit zone thresholds (mA)	0 ÷ 2
Normal mode zone power supply and thresholds (mA)	2 ÷ 10

**GENERAL DATA**



**43CPC004EN**

**ERACLE CONVENTIONAL CONTROL PANEL WITH 4 ZONES**

Notifications

Led