



## Hard wired intruder alarm **Scantronic 9448**



**COOPER** Safety

### Easy to install, saving you time and money

Simple wiring configuration  
Easy to program

### Upgradeable to a communicating system for extra security

Option to add SD1, SD2 or SD-GSM speech dialler to create a communicating system

### Easy to operate

Each system has full and part set facilities, the ability to change access codes and remote keypads to give a high level of security and total peace of mind

### Designed to offer exceptional value for money

Ideal choice for low security risk applications

## Product Compatibility

Model	Description
Zones	7 closed circuit (zone 7 pre-programmed as entry/exit)
Zone Attributes	Personal attack, normal alarm, chime, omit, not used, part set omit, fire, entry route
Panel	9448EUR-90 endstation control panel with onboard tactile illuminated rubber keypad 9448EUR-95 endstation control panel with remote tactile illuminated rubber keypad
Keypads	Accepts up to 2 remote 9427 Style keypads. Dual key personal attack (PA)
Display	10 LED indicators on the control panel, including day (unset) LED
Anti-tamper circuits	Global
Event Log	10 events recorded
Expansion	No
Full/part set	Fully programmable part set option
Panel siren	Yes
Internal Sounder	Accepts 1 x 16 Ω internal sounder
Outputs	Bell and strobe 500mA open collector. 1 programmable 100mA as PIR set latch or shock sensor reset
Bell duration	Programmable up to 20 minutes
Entry/exit times	5 programmable entry and exit times
Battery	2.1Ah lead acid gel type rechargeable
12v power	Quiescent Panel: 55mA Keypad: 20mA
Aux DC power	500mA @ 13.8v
Dimensions	Control panel (H x W x D): 212 x 212 x 68mm. Keypad (H x W x D): 100 x 120 x 28mm
Weight	Control panel: 1.2kg
Temperature range	-10°C to +55°C
Communication output	Personal attack (PA) and burg (for speech diallers only)
Compatibles	Control panel operates with all types of detectors, bells and sirens
Scantronic compatible equipment	09427EUR-80 remote keypad, 9040 16 Ω internal siren, SD1, xcel PIR detector




9448EUR-95 (remote keypad)



9448EUR-90 (on board keypad)

Installer Details :



For information on your local stockist  
contact our Marketing Department

telephone: +44 (0)1594 541 979  
fax: +44 (0)1594 545 445  
email: [marketing@coopersecurity.co.uk](mailto:marketing@coopersecurity.co.uk)