



## AFI5100

SiPass®  
integrated

### Input point module including base plate

- 
- **Support for up to 32 passive input devices**
  - **Input supervision**
  - **4 auxiliary outputs**

The AFI5100 is a programmable input controller used as part of a SiPass integrated system. It provides a local interface between the central controller (AC5100, AC5102 or AC5200) and the devices used to monitor a facility, such as infrared detectors.

When an input device that is connected to an AFI5100 changes status, the AFI5100 registers the status change and forwards this data to the central controller. After checking the validity of the data, the central controller sends the message to the SiPass integrated server, so the alarm-handling mechanism can respond appropriately.

## Features

---

- Support for up to 32 passive input devices
- 4 auxiliary outputs (relay)
- Auxiliary 12V DC output power supply
- Local anti-tamper input and alarm output
- Input supervision
- Communications status LEDs for both transmitting and receiving
- Activity status LED
- Power status LED
- Flash memory updateable
- Support for enhanced fire override

## Description

---

The AFI5100 has 32 input ports onboard for the connection of a wide variety of alarm and monitoring devices. Each input can be supervised individually to ensure that an alarm is reported instantly if tampering is detected.

The AFI5100 also includes four auxiliary relay output connections to make it possible to connect peripheral devices like strobes or alarm buzzers to enhance the security of the installation.

The ATI5100 provides full support for enhanced fire override. This technology greatly improves security by discerning false fire override events from the real thing, preventing intruders from forcing a fail-safe scenario and thereby possibly gaining access.

The AFI5100 is programmed with the latest flash memory and can therefore be updated with ease via the field level network (FLN) configurator software.

## Technical data

---

<b>AFI5100</b>	
Interface	To controller: RS485
Operating voltage	12 to 24V DC ±20 %
Power consumption	50 W
Inputs	32 x internally supplied (supervised or unsupervised) 1 x Tamper (internally supplied) 1 x Fire override (potential-free or internally supplied)
Outputs	4 x Auxiliary relays (30V DC, 2 A) 1 x Alarm output (open-collector 12V DC, 200 mA) 1 x Fire override relay (30 V DC, 2
Firmware	Flash upgradeable
Indicators	Power, Activity, Communication Inputs, Output Peripheral supplies Fire override
Operating temperature	0 to +50 °C
Dimensions (W x H x D)	250 x 287 x 30 mm
Approval	CE, UL294, C-Tick

## Details for ordering

---

Type	Part no.	Designation	Weight
AFI5100	V6FL7820-8CB10	Input point module including base plate	1.35 kg

Issued by  
Vanderbilt International (IRL) Ltd.  
Clonshaugh Business and Technology Park  
Clonshaugh  
Dublin 17  
Ireland

© 2020 Copyright by Vanderbilt International (IRL) Ltd.

Data and design subject to change without notice.  
Supply subject to availability.

[www.vanderbiltindustries.com](http://www.vanderbiltindustries.com)

---

Document no. **A-10717**

Edition 09.06.2020