



## DOORPROTECT PLUS



Wireless opening detector notifies of first signs of intrusion into the room through the door or window. It is installed even on roof windows which can be left open when leaving the house.



Ready to operate straight out the box: the battery is already installed, therefore there is no need to disassemble the detector. With one click, it can be connected to the hub in the mobile application. It can be mounted on the SmartBracket in just a few minutes.

## Specification

Classification	Combined point magnetic contact and vibration radio channel security detector
Type of detector	Wireless
Installation method	Indoors
Compatibility	Operates only with Hub, Hub Plus and ReX
Sensing element	Reed switch, accelerometer
Alarm signal delivery time	0.15 s
Activation threshold	Small magnet — 1 cm, Big magnet — 2 cm
Power supply	Battery: CR123A battery, Power supply voltage: 3 V Battery life — up to 5 years
Jeweller radio technology	Communication range with central unit — up to 1,200 m in an open space Two-way communication between devices Operating frequencies — 868.0—868.6 MHz Self-adjusting RF output power — up to 20 mW Block encryption based on AES algorithm Device polling period — 12-300 s
Temperature sensor	Available
Operating temp range	From +5°C to +40°C
Permissible humidity	Up to 75%
Anti-sabotage	Protection against fraud Jamming detection Tamper-resistant
Remote setting and testing	+
Dimensions	Diameter: 20 mm Height: 90 mm
Weight	29g
Certification	Grade 2, CE
Complete set	DoorProtect Plus opening detector SmartBracket mounting panel Two magnets CR123A battery (pre-installed) External contact Installation set User's guide