



1424

## DIGITAL SWITCHING DEVICE FOR SIMPLEBUS TOP



Switching device 1424 can be used to create Simplebus systems of up to 120,000 users. It can also be used to create multi-kit systems up to 500 Comelit Simplebus KITS that can be integrated into a Simplebus system. The device also makes it possible to include main and secondary switchboards within a system (which can be called independently) and offers alarm signals to those particular switchboards. It offers options to cascade the bus line distribution as an alternative to star distribution, optimising the cabling for the part of the system before the mixers 4888 and 4888C. It also has a self-powering function for the LSILS input, which allows riser management without requiring a dedicated secondary external unit. Power supply 12Vac (part. 1200 may be used) -20Vdc. 4 DIN modules. Dimensions 60x85x35mm.



**1424**

## DIGITAL SWITCHING DEVICE FOR SIMPLEBUS TOP

### MAIN FEATURES

Product height (inch):	3.35
Product width (inch):	2.36
Product depth (inch):	1.38
Operating temperature (°F):	41 ÷ 104
DIN rail mounted:	Yes
DIN modules (no.):	4
Maximum current absorption (mA):	80

### COMPATIBILITY

Simplebus Top audio/video system:	Yes
Simplebus 1 audio system:	Yes

### AUDIO/VIDEO FEATURES

Audio system:	Yes
Audio/video system:	Yes