

## 8 MDS SENSOR DECODER



### Reference: 02429

This decoder is designed to work only with MDS-Digital and CAC systems.

It has 8 sensor inputs that can be configured for use as NO sensor (with contact normally open) or NC (contact normally closed),...

### DESCRIPTION

This decoder is designed to work only with MDS-Digital and CAC systems.

It has 8 sensor inputs that can be configured for use as NO sensor (with contact normally open) or NC (contact normally closed), achieved by means of a jumper located beside each input.

In both cases, signal activation can be sent from the central unit in real time (instantly) or with delay, depending on the choice of the "timing" parameter that controls the time that the sensor must be activated to generate an alarm signal.

DIN-10 rail format for easy installation inside an electrical equipment box, or can be screwed directly onto the wall.

MDS Digital system: Simplified BUS installation digital audio and video door entry system that lets you manage buildings and residential complexes of unlimited size and able to integrate all the community services:

- Audio and Video Door Entry Systems
- Intercommunication between accesses.
- Access Control
- Centralized and automated security

Requires Central Unit/s to manage the installation (Capacity per UC: 9999 homes, 32 accesses/guard units. Can link up to 63 UCs). Can be either general entrances or interior blocks.

MDS systems require floor Decoders to connect the homes to the installation BUS and act as insulators. Home-panel communication is private.

Wiring:

- Audio: 6-wire bus.
  - Video: audio bus + Coaxial (video) + 2 power supply wires.
- Maximum distance in the installation depending on the cable section used (see technical manuals).

Centralized CAC Access Control System. Composed of one part hardware: CAC central units, readers, decoders, etc. and one part software that lets you configure and manage the installation, by means of installer applications and multi-post user.

Restricts access to certain private zones of a facility (office, warehouse, factory, sports area) to those persons not in possession of a authorized credential or identification.

Enables complete management of an installation with several doors and advanced access control functions: restrictions by user groups, both spatial (areas) and temporal (schedules), anti-passback function, capacity limitation, greater user capacity, activation of devices from the reader, recording of incidents for consultation later, control or security centre.

In contrast with other systems, CAC access control lets you integrate other complementary functions with no need for additional controllers:

- Vehicle control.
- Double Anti-passback.
- Intercommunication. For those accesses where we have to allow access to other people from outside the facility. By pressing a button we contact the control centre and access is permitted from there.
- Technical or intruder alarms. Each entrance and exit can be programmed with a detection and action time.
- Automation. Weekly programmer which can schedule up to 32 daily activations of relays and arming of sensors, individually or in groups.

The user information and associated restrictions are stored in a CAC Central Unit that takes the decisions to permit or deny access. In facilities that exceed these specifications (more readers or users) up to 63 central units can be grouped together.

Reader wiring: 2 wires + screened twisted pair

Intercommunication wiring. 4 wires + screened twisted pair

## TECHNICAL SPECIFICATIONS

Power supply: 12 Vdc  
Consumption: 40 mA  
8 configurable NO / NC inputs

Requires programming.

LED status indicator  
- OFF: the decoder has not yet been programmed.  
- ON: the decoder is in programming mode.  
- - BLINKING: the decoder has been coded and is working.

DIN 10 dimensions: 175x 90 mm x60 mm

Power supply:  
- Audio: 12 Vdc  
- Video: 18 Vdc

Power supply: 12 Vdc

**Weight:** 0,3000344 kg

**Size of product when packed:** 6,5x18x10 cm

**EAN 13:** 8424299024295

---