

4/W MDS VIDEO DISTRIBUTOR

**Reference:** 2418

DIN-10 rail format for easy installation inside an electrical equipment box, or can be screwed directly onto the wall.

DESCRIPTION

DIN-10 rail format for easy installation inside an electrical equipment box, or can be screwed directly onto the wall.

MDS Digital system: Simplified BUS installation digital audio and video door entry system that lets you manage buildings and residential complexes of unlimited size and able to integrate all the community services:

- Audio and Video Door Entry Systems
- Intercommunication between accesses.
- Access Control
- Centralized and automated security

Requires Central Unit/s to manage the installation (Capacity per UC: 9999 homes, 32 accesses/guard units. Can link up to 63 UCs). Can be either general entrances or interior blocks.

MDS systems require floor Decoders to connect the homes to the installation BUS and act as insulators. Home-panel communication is private.

Wiring:

- Audio: 6-wire bus.
 - Video: audio bus + Coaxial (video) + 2 power supply wires.
- Maximum distance in the installation depending on the cable section used (see technical manuals).

TECHNICAL SPECIFICATIONS

The video distributors are activated by the corresponding decoder via the "V" terminal. The distributors include a bridge under the left cover, which will need to be cut in all the distributors except in the last one of each branch. Power supply: 18 Vdc Input impedance: 75 ohms.

DIN 10 dimensions: 175x 90 mm x60 mm

Power supply:

- Audio: 12 Vdc
- Video: 18 Vdc

Weight: 0,245643 kg

Size of product when packed: 6,3x17,7x9,5 cm

EAN 13: 8,4243E+12