

Controlsoft® RF Reader

Part Code: CS-AC-1800



The CS-AC-1800 from Controlsoft is an attractive RF Reader, for use with Controlsoft CS-AC-7302 Two Button and CS-AC-7304 Four Button Handheld Transmitters. The CS-AC-1800 connects to an Access Control Unit via an industry standard Wiegand connection.

Features and Benefits

- Read range up to 20m
- Electronics Potted for Environmental Protection
- Tri-colour LED and buzzer for user feedback
- Suitable for Indoor or Outdoor Use
- Dimensions: 119mm x 42mm x 22mm

Technical

- Housing rated to IP68
- Wiegand 26bit format
- Frequency: 868Mhz
- Wiegand Interface
- 12Vdc @ 50mA
- Operating temperature: -20 °C to +60°C
- Operating humidity: 0 to 95% non-condensing
- 2 Year Warranty

www.controlsoft.com

© 2013 Controlsoft Limited. All rights reserved. Controlsoft and the Controlsoft logo are registered trademarks of Controlsoft Limited in Europe, the U.S. and/or other countries. All other trademarks, service marks, and product or service names are trademarks or registered trademarks of their respective owners.

9030-0005 March 2013

